

Quantum hacking: adding a commercial actively-quenched module to the list of single-photon detectors controllable by Eve

V. Makarov*

*Department of Electronics and Telecommunications,
Norwegian University of Science and Technology, NO-7491 Trondheim, Norway*

A. Anisimov

*Radiophysics Department, St. Petersburg State Polytechnical University,
Politechnicheskaya street 29, 195251 St. Petersburg, Russia*

S. Sauge

*Department of Microelectronics and Information Technology,
Royal Institute of Technology (KTH),
Electrum 229, SE-16440 Kista, Sweden*

(Dated: March 21, 2009)

We show how PerkinElmer SPCM-AQR actively-quenched detector module can be controlled by an eavesdropper. The scheme uses bright optical pulses to get the detector blinded. In this mode, one can trigger a detector click controllably (with sub-nanosecond time jitter) if one applies at its input another bright optical pulse above some intensity threshold. This loophole may be exploited to launch an intercept-resend (faked-state) attack against quantum cryptosystems using these detectors. An example is given in the case of a four-state protocol implemented with polarization coding.

Over the past twenty years, quantum key distribution (QKD) has progressed from a tabletop demonstration to commercially available systems and experiments with secure key exchange possible up to 100 km and growing.¹ Security of these cryptosystems is based on the impossibility, in principle, to reliably copy an a-priori unknown quantum state, as accounted for by the no-cloning theorem. However, security also relies on the assumption that the electro-optical devices which are part of quantum cryptosystems do not deviate from model assumptions made to establish security proofs.^{2,3} This second range of security threats, which target component imperfections, has already been successfully exploited by one of the authors to take control of widely used single photon detectors, namely InGaAs-based modules at telecom wavelengths⁴ and silicon-based (Si) modules in the 500–900 nm wavelength range.⁵ In the latter case, the controlled modules used passively quenched avalanche photodiodes (APDs). However, among the 26 reported experiments employing Si APDs, roughly half use active quenching.⁵ Until recently, PerkinElmer SPCM-AQR module and its four-channel version (SPCM-AQ4C) have been the only commercially available Si single-photon detector models. In this Letter, we show that the SPCM-AQR module can also be controlled by an eavesdropper. The attack exploits the generic “blinding” behavior of such APDs, whose single-photon sensitivity can drop to *exactly* zero when illuminated well above single photon level⁵ (optical peak powers used here are between 1 and

10 mW at 780 nm).

The part of the detector electrical circuit relevant to the understanding of the presented control method is shown in Fig. 1. To the left of the APD is a high-voltage power supply circuit. In normal single-photon regime, it provides stable bias voltage at the cathode of the APD (the two detector samples we tested had stable bias voltages of 350 V and 410 V, respectively). To the right of the APD is a circuit which senses the onset of avalanches. Active quenching is accomplished by connecting the anode of the APD to +30 V, with the effect of lowering the voltage across the APD below the breakdown voltage. 20 ns after quenching, the circuit is reset by briefly connecting the anode of the APD to the ground.

When the APD is illuminated by a bright optical pulse, the current through it is much larger than during an ordinary single-photon avalanche. A current limiting circuit connected to the cathode of the APD kicks in and limits the current pulse to about 10 mA. This current is drawn from the decoupling capacitor C9, whose other end is connected to the output of a low-power operational amplifier (OA) U7.1 (Texas Instruments TLC2262). This OA is relatively slow and has a maximum load current significantly lower than 10 mA. Over the next microsecond following the current pulse that exceeds the OA load capacity, its output voltage produces a 1 V deep dip. As it turns out, this output voltage controls, through a high-power MOSFET Q11, a miniature high-voltage DC/DC converter module U6. In result, when the APD is illuminated by bright optical pulses with a certain frequency (typically above 70 kHz), the input power of U6 gets disrupted with the same frequency. Inside U6, the switching circuit appears to phase lock or fractionally phase lock to

*Electronic address: makarov@vad1.com




FIG. 1: PerkinElmer SPCM-AQR module. Equivalent diagram of the high-voltage power supply, avalanche sensing and quenching circuitry (reverse engineered from sample with PCB labeled “EG&G P/N 2580883 rev. G”).

the frequency of disruptions, so that U6 significantly reduces its output voltage, depending on the frequency and intensity of the optical pulses, as shown in Fig. 2. When the APD bias voltage drops by more than 12–14 V, the rate at which the detector clicks becomes *exactly* equal to the frequency of the optical pulses. In other words, between two consecutive pulses (denoted as control pulses thereafter), the detector becomes *totally insensitive to single photons, dark counts and afterpulses*, producing no extra clicks whatsoever. In contrast, outside of the complete control range, it produces random clicks at a typically much higher rate than the control pulses.

While the detector is blinded between two control pulses of sufficient frequency and peak power, it is possi-




FIG. 2: (Color online) APD bias voltage vs. frequency and peak optical power P_{control} of rectangular 50 ns wide input optical pulses. Normal bias voltage at low count rate for this detector sample is 350 V. Filled symbols denote pulse parameters at which the detector got under complete control, see text. The control pulses do not have to be very regular to get the detector under control. Actually, a fast deeply frequency modulated pulse sequence works too.

ble to make it click *controllably* if one applies at its input a shorter pulse above a certain intensity threshold. This is illustrated in Fig. 3. It shows that in the so-called “blinded” mode, pulses of 8 ns typical width trigger a detector click with unity probability and sub-nanosecond time jitter at a nominal peak power (case a), while at




FIG. 3: (Color online) Oscillogram at detector output (blue trace) illuminated by bright optical pulses (red trace) made of control pulses (8.5 mW, 50 ns wide, 230 kHz repetition rate) to blind the detector, and of weaker trigger pulses (8 ns wide), which make the detector click with unity probability and sub-nanosecond time jitter *only* above a certain intensity threshold (detector always clicks in case a, never clicks in case b).




FIG. 4: (Color online) Intercept-resend (faked-state) attack Eve could launch against a QKD system which runs a four-state protocol with polarization coding and passive choice of basis. In the example, Eve targets the detector recording vertically polarized qubits, in the horizontal/vertical (H/V) basis. Eve sends (1) control pulses with an incoherent mixture of H and V polarizations (to keep all four detectors blinded when she is not sending faked states) and (2) a faked state with V polarization and intensity I_0 set slightly above the threshold after basis choice to address the target detector. The detectors recording H and V polarized qubits in the conjugate (45° rotated) basis will each receive a pulse of intensity $I_0/2$ below the threshold, and thus will remain blinded. In the diagram: BS, beamsplitter; PBS, polarizing beamsplitter; HWP, half-wave plate.

slightly more than half this intensity, the detector remains blinded (case b).¹² This feature is the last missing ingredient Eve needs to stage a successful intercept-resend (faked state) attack² on a QKD system using such detectors.

As an example, let us consider a QKD system which runs a four-state protocol with polarization coding and passive choice of basis at the receiver side (Bob), as is often the case with QKD systems using Si detectors.⁵ This is illustrated in Fig. 4. We assume Eve owns an exact replica of Bob's detection apparatus, with which she intercepts and measures the polarization state of each qubit sent by Alice. In order to run a successful attack, Eve must resend faked states that will force her detection results onto Bob in a transparent way. Provided that all four detectors are blinded by her control pulses, Eve can send an optical pulse in the quantum state corresponding to the target detector (e.g., vertically polarized pulse with peak power right above the intensity threshold). In the conjugate basis, the 45° rotated pulse will be split equally at the PBS, and with pulse intensities reduced by half (thus below the threshold) the detectors will remain blinded.

The attack should also work with active choice of basis (in this case, the target detector will click if Bob

chooses the same basis as Eve, and otherwise his two detectors will remain blinded). The attack should as well be successful if decoy states are used, since Eve does not launch any photon-number splitting attack here.⁶ The only thing that betrays her presence is the simultaneous arrival at all detectors of the control pulses with a rate of at least 70 kHz. In some QKD systems, these may be ignored by Bob as falling outside his post-processing gating time window. In free-space systems operating in daylight, these pulses may be mistaken by Bob for normal background count rates.

As we write this Letter, one other control mode has been uncovered with this detector (to be reported soon), and we anticipate other vulnerabilities to be exploitable by Eve. We think that use of PerkinElmer detectors as they are in QKD systems does not guarantee security. Several reported experimental QKD systems using these detectors are potentially vulnerable.^{7,8,9,10,11} Identifying and patching such loopholes is a required process to bring realistic implementations at the level of unconditional security envisioned by theoretical proofs.^{2,3}

The authors wish to thank Johan Waldeback for help in reverse-engineering the detector. Financial support from the ECOC'2004 foundation and the Research Council of Norway (grant no. 180439/V30) is acknowledged.

¹ Commercial QKD systems are available, as of early 2009, from at least three companies: id Quantique (Switzerland), <http://www.idquantique.com/>; MagiQ Technologies (USA), <http://www.magiqtech.com/>; SmartQuantum (France), <http://www.smartquantum.com/>.

² H.-K. Lo and Y. Zhao, arXiv:0803.2507 [quant-ph].

³ V. Scarani, H. Bechmann-Pasquinucci, N. J. Cerf, M. Dušek, N. Lütkenhaus, and M. Peev, arXiv:0802.4155 [quant-ph].

⁴ V. Makarov, A. Anisimov, and J. Skaar, Phys. Rev. A **74**,

022313 (2006).

⁵ V. Makarov, arXiv:0707.3987v2 [quant-ph].

⁶ W.-Y. Hwang, Phys. Rev. Lett. **91**, 057901 (2003).

⁷ C. Erven, C. Couteau, R. Laflamme, and G. Weihs, Opt. Express **16**, 16840 (2008).

⁸ V. Fernandez, R. J. Collins, K. J. Gordon, P. D. Townsend, and G. S. Buller, IEEE J. Quantum Electron. **43**, 130 (2007).

⁹ X. Shan, X. Sun, J. Luo, Z. Tan, and M. Zhan, Appl. Phys. Lett. **89**, 191121 (2006).

- ¹⁰ K. J. Resch, M. Lindenthal, B. Blauensteiner, H. R. Böhm, A. Fedrizzi, C. Kurtsiefer, A. Poppe, T. Schmitt-Manderbach, M. Taraba, R. Ursin, et al., *Opt. Express* **13**, 202 (2005).
- ¹¹ W. T. Buttler, R. J. Hughes, S. K. Lamoreaux, G. L. Morgan, J. E. Nordholt, and C. G. Peterson, *Phys. Rev. Lett.* **84**, 5652 (2000).
- ¹² The actual value of the intensity threshold depends on the timing of the trigger pulse relative to the other optical pulses. The intensity thresholds were identical for the first two detector samples we have tested; however for a third detector sample that was manufactured several years later the threshold values were different.